

DS-96000NI-I16/H SERIES NVR



Features and Functions

Professional and Reliable

- New logical and visualized GUI design.
- · Adopts professional embedded hardware and software, and pioneering dual-OS design to ensure the reliability of system running.
- Supports redundant power supply to improve the system stability.
- Supports HDD hot swap with RAID0, RAID1, RAID5, RAID 6, and RAID10 storage scheme configurable.
- Either normal or hot spare working mode is configurable to constitute an N+1 hot spare system.

Video Input and Transmission

- Up to 128/256 IP cameras can be connected.
- Supports live view, storage, and playback of the connected camera at up to 12 megapixels resolution.
- H.265+ compression effectively reduces the storage space by up to 75%.
- 4 self-adaptive 10M/100M/1000M network interfaces.
- Adopt stream over TLS encryption technology (enhanced SDK service and RTP over HTTPS protocol)
- Connectable to the third-party network cameras like ACTI, Arecont, AXIS, Bosch, Brickcom, Canon, ONVIF, PANASONIC, Pelco, SAMSUNG, SANYO, SONY, Vivotek and ZAVIO.

HD Output

- Simultaneous HDMI 1/VGA output as the main output and the HDMI 2 works as the auxiliary output.
- HDMI and VGA1 simultaneous outputs by default. Asynchronous outputs configurable.
- Video outputs at up to 4K (4096×2160) resolution.
- Supports decoding up to 20 channels at 1080p resolution.

Storage and Playback

- Up to 16 SATA interfaces and 1 eSATA interface provided for HDD connection
- 10 TB capacity for each HDD.
- HDD health monitoring.
- Supports HDD quota and group modes; different capacity can be assigned to different channels.
- Normal/Important/Custom video playback.

Various Applications

- Centralized management of IP cameras is supported, including configuration, information import/export, real-time information display, two-way audio, upgrade, etc.
- Connectable to smart IP cameras from Hikvision and the recording, playing back, and backing up of VCA alarms can be realized.
- VCA detection alarm is supported.
- VCA search for facial detection, behavior analysis, people counting and heat map.
- Supports starting record with one key.
- Realizes instant playback for assigned channel during multi-channel display mode.
- Smart search for the selected area in the video; and smart playback to improve the playback efficiency.





Specifications

| Model | | DS-96128NI-I16/H | DS-96256NI-I16/H | | |
|---------------|-----------------------------------|---|--|--|--|
| Video & Audio | IP video input | 128-ch | 256-ch | | |
| input | Incoming/outgoing | 768 Mbps/512 Mbps | 768 Mbps/768 Mbps | | |
| | bandwidth | | | | |
| | Incoming/outgoing | 768 Mbps/512 Mbps | 768 Mbps/768 Mbps | | |
| | bandwidth (RAID mode) | | | | |
| | TLS outgoing bandwidth | 128 Mbps, or 64 Mbps (when RAID is enabled) | | | |
| | Protocol | HIKVISION, ACTI, ARECONT, AXIS, BOSCH, BRICKCOM, CANON, HUNT, ONVIF (Version 2.5), | | | |
| Video & Audio | LIDAM subsub | PANASONIC, PELCO, RTSP, SAMSUNG, SONY, VIVOTEK, ZAVIO | | | |
| output | HDMI output | Two independent HDMI outputs of 4K resolution. Resolution: 4K (4096 × 2160), 4K (3840 × 2160)/30Hz, 2K (2560 × 1440)/60Hz, 1080p (1920 × 1080)/60Hz, UXGA (1600 × 1200)/60Hz, | | | |
| σατρατ | | | | | |
| | VGA output | SXGA (1280 × 1024)/60Hz, 720p (1280 × 720)/60Hz, XGA (1024 × 768)/60Hz | | | |
| | ναλ σαιραί | 1-ch. Resolution: 1080p (1920 × 1080) /60Hz, UXGA (1600 × 1200) /60Hz, SXGA (1280 × 1024) /60Hz, 720p (1280 × 720) /60Hz, XGA (1024 × 768) /60Hz | | | |
| | LCD output (optional) | | | | |
| | Audio output | One 7 inch LCD | | | |
| Video & Audio | ' | 1-ch. RCA (2.0 Vp-p, 1 KΩ) | | | |
| decoding | Decoding format Video resolution | H.265, H.265+, H.264, H.264+,MPEG4, MJPEG (for Hikvision IP camera only) 12 MP/8 MP/7 MP/6 MP/5 MP/4 MP/3 MP/1080p/UXGA/720p/VGA/4CIF/DCIF/2CIF/QCIF | | | |
| decoding | | | USODY UNGAY / ZUDY VGAY4CIF/ DCIF/ ZCIF/ CIF/ QCIF | | |
| | Synchronous playback | Up to 16 channels | | | |
| | Capability | 3-ch@12 MP (30fps), 5-ch@8 MP (30fps), 6-ch@6 MP (30fps), 10-ch@4 MP (30fps), | | | |
| | late of a c | 20-ch@1080p (30 fps) | | | |
| HDD | Interface | 16 SATA interfaces supporting hot-plug | | | |
| HDD | Capacity | Up to 10 TB for each HDD | | | |
| DAID | Storage extension | 1 × eSATA interface, 2 × mini SAS interface (optional) | | | |
| RAID | RAID Type | | RAID0, RAID1, RAID5, RAID 6, and RAID10 | | |
| Network | Protocol | IPv6, HTTPS, UPnP, SNMP, NTP, SADP, SMTP, NFS, iSCSI, PPPoE, DDNS | | | |
| management | Network interface | 4, RJ45 10M/100M/1000M self-adaptive Ethernet interface | | | |
| | Two-way audio input | 1-ch, RCA (2.0 Vp-p, 1 KΩ) | | | |
| | Serial port | RS-232; RS-485; Keyboard | | | |
| | USB interface | Front Panel: 2 × USB 2.0; Rear Panel: 2 × USB 3.0 | | | |
| External | Alarm input/output | 16/8 | | | |
| interface | Decoding board | 1 | | | |
| | Extension board (optional) | | 10M/100M/1000M optical interfaces (1.25 Gbps | | |
| | | SFP module), eight RS-485 interfaces, and alarm interface of 32 alarm inputs and 16 alarm | | | |
| | | outputs. | | | |
| | Power supply | 100 to 240 VAC, 550W | | | |
| | Fan | Redundant dual ball bearing fan; Speed adjus | table; Hot-plug | | |
| General | Consumption (without | ≤ 140W | | | |
| | HDD) | | | | |
| | Working temperature | 0 °C to + 50 °C (32 °F to 122 °F) | | | |
| | Working humidity | 10% to 90% | | | |
| | Dimension (W × D × H) | 442 × 494 × 146 mm (17.4 × 19.4 × 5.7 inch) | | | |
| | Weight (without HDD) | ≤ 16 kg (35.3 lb) | | | |




Specifications

| Model | | DS-96128NI-I16/H | DS-96256NI-I16/H | |
|--------------------------|-----------------------|---|------------------|--|
| Video wall management | HDMI output/input | 6/1 | | |
| | HDMI output | 4K(3840x2160)/60Hz, 4K (3840x2160)/30Hz, 2K (2560x1440)/60Hz, 1080p (1920x1080)/60Hz, | | |
| | resolution | SXGA (1280x1024)/60Hz, 720p (1280x720)/60Hz, XGA (1024x768)/60Hz | | |
| | HDMI input resolution | 1080p (1920x1080), SXGA (1280x1024), 720p 1280x720), XGA (1024x768) | | |
| | Decoding capacity | 48-ch@1080p | | |
| | Decoding resolution | 12 MP/8 MP/7 MP/6 MP/5 MP/3 MP/1080p/UXGA/720p/VGA/4CIG/DCIF/2CIF/CIF/QCIF | | |
| | Collage | Supported | | |
| | Auto-switch | Supported | | |
| | Open window | Supported | | |
| | Layer overlay | Supported | | |
| | Window roaming | Supported | | |
| | Display local signal | Supported | | |
| | source on video wall | | | |



Physical Interfaces



| No. | Name | No. | Name | |
|-----|-------------------------------|-----|--------------------|--|
| 1 | HDMI 1/2 Video Output | 9 | RS-232 Interface | |
| 2 | Audio Input | 10 | Alarm Input | |
| | Audio Output | | Alarm Output | |
| 3 | USB 3.0 | 10 | RS-485 Interface | |
| 4 | LAN | | Keyboard Interface | |
| 5 | eSATA Interface | 11 | Ground | |
| 6 | VGA Video Output | 12 | Power Supplies | |
| 7 | Mini SAS Interface (Optional) | 13 | Decoding board | |
| 8 | Reset Button | | | |

Available Models

DS-96128NI-I16/H; DS-96256NI-I16/H

| Distributed by | |
|----------------|--|
| | |
| | |
| | |
| | |
| | |
| | |

HIKVISION

Headquarters

No.555 Qianmo Road, Binjiang District, Hangzhou 310051, China T+86-571-8807-5998 overseasbusiness@hikvision.com

Hikvision USA T +1-909-895-0400 sales.usa@hikvision.com

Hikvision Italy T +39-0438-6902 info.it@hikvision.com

Hikvision Singapore T +65-6684-4718 sg@hikvision.com

Hikvision Africa T +27 (10) 0351172 sale.africa@hikvision.com

Hikvision Europe T +31-23-55-42-770 info.eu@hikvision.com

Hikvision France T +33(0)1-85-330-450 info.fr@hikvision.com

Hikvision Oceania T+61-2-8599-4233 salesau@hikvision.com

Hikvision Hong Kong T +852-2151-1761

Hikvision Middle East T +971-4-8816086 salesme@hikvision.com

Hikvision Spain T +34-91-737-16-55 info.es@hikvision.com

Hikvision Canada T+1-909-895-0400 sales.usa@hikvision.com

Hikvision Russia T +7-495-669-67-99 saleru@hikvision.com

Hikvision Poland T +48-22-460-01-50 poland@hikvision.com

Hikvision Korea T+82-31-731-8841 sales.korea@hikvision.com

Hikvision India T +91-22-28469900 sales@pramahikvision.com

Hikvision UK T+01628-902140 support.uk@hikvision.com

Hikvision Brazil T+55 11 3318-0050 Latam.support@hikvision.com